<u>Step 1</u>

Open your Internet Browser and type 192.168.0.1

Then Username: admin , Password: admin

🥹 Mozilla Fire	fox					
<u>File E</u> dit <u>V</u> iew	Hi <u>s</u> tory <u>B</u> ookn	narks <u>I</u> ools <u>H</u> elp				
$\langle \cdot \rangle $	C 🗙 👍	192.168.0.1				
횓 Most Visited 🦉	Google Trans	late 📄 ENDY SYSTEM HOME 🚥 ENDY AUSTRALIA - All 頭 Engenius Singapore N 📔 EnGenius /	Australia 🚥 = Wellcome to			
📄 ds_SMCWBR14S-N4-AS.pdf (applicatio 🔟 📄 ::SMC Networks Asia :: 🛛 🔯 🏠 Loading 🔯 👘 🔛						
	Authentication Required					
	?	A username and password are being requested by http://192.168.0.1. The site says: "Default: admin/admin"				
	User Name:					
	Password:					
		OK Cancel				

You will see the status page, and you can see your current Firmware Kernel Version and Application Version

	Wireless-N Pocket AP/Router AP Router Mode
EnGenius	Status LAN DHCP Schedule Log Monitor Language
ETR9350	
System	You can use the Status page to monitor the connection status for the WAN/LAN interfaces, firmware and hardware version numbers, any illegal attempts to access your network and information on all DHCP client PCs currently connected to your network.
Wizard	System Model 3G Wireless Travel Router
Internet	Mode AP Router
internet	Uptime 16 min 6 sec
Wireless	Current Date/Time 2009/01/01 00:16:06
Firewall	Serial Number 101200239
Advanced	Kernel version 1.0.7
Auvanceu	Application version 1.0.7
Tools	WAN Settings
	Attain IP Protocol Mobile 3G
	SIM Status Ready
<mark>;_</mark> ((_A))	

<u>Step 2</u>

Then Click on Tools and click Firmware



*From EnGenius official website download the Latest Firmware version prior to upgrade within the zip/rar file you can find out 2 files

- 1. ETR9350-APPS-V1-0-7-91.dlf
- 2. ETR9350-KNL-V1-0-7-91.dlf

<u>Step 3</u>

Then Click on Browse and Select ETR9350-KNL-V1-0-7-91.dlf and Click Apply for upgrade your Kernel Firmware

		Wireless-N Pocket AP/Router APRouterMode				
	EnGenius	Admin Time DDNS Power Diagnosis Firmware Back-up Reset				
	System	You can upgrade the firmware of the router in this page. Ensure, the firmware you want to use is on the local hard drive of your computer. Click on Browse to browse and locate the firmware to be used for your update.				
	Wizard					
	Internet					
	Wireless	Apply				
	Firewall	(the second sec				
	Advanced					
	Tools					
	3 6 ())	Ultra Portable WPS WiFi Multi Media				
After Click Apply it will automatic POP-Up the message box Click OK						
		Wireless-N Pocket AP/Router AP RouterMode 💌				
	EnGenius	<u>Admin Time DDNS Power Diagnosis Firmware Back-up Reset</u>				
	2110500	You can upgrade the firmware of the router in this page. Ensure, the firmware you want to use is on the local hard drive of your computer. Click on Browse to browse and locate the firmware to be				
	System	used for your update.				
	Wizard	The page at http://192.168.0.1 says:				
	Internet	Po you wish to continue with the upgrade process?				
	Wireless	OK Cancel Apply Cancel				
	Firewall					
	Advanced					
	Tools					

After Firmware Upgrade, the router going to reboot by itself



Then automatically go back to the Status page

<u>Step 4</u>

After that, same process as <u>Step 2 and Step 3</u> Click on **Tools** and click **Firmware**

Then Click on Browse and Select ETR9350-APPS-V1-0-7-91.dlf and Click Apply for upgrade your Application Firmware

After Firmware Upgrade, the router will going to reboot by itself, then automatically go back to the Status page again. And the Firmware is completely upgraded as firmware version 1.0.7 like following

